



CLASS BOOSTER 150A



Input Voltage 1Ph 230 Volt
Battery 12 Volt, 20 > 200 Ah



Description

- Code: 340600

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- Charging current regulation**
- Overload protection**
- Inversions of polarity protection**
- Short circuits protection**
- Manual charge breaker**

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12V

Power (KW): 0,3 - 1,2Kw

Average charging current (Amp): 12,0A

Effective charging current (Amp): 18,0A

Battery capacity (Ah min/max): 20 / 200Ah

Charging positions (N°): 2

Boosting Current (Amp 0 Volt CC): 135A 0V

Boosting current (Amp 1 Volt / EL): 100A 1V

Weight Kg $\approx$: 6.5

Dimension, Wid.-Dep.-Height (mm): 200 x 190 x 270

LOGISTIC INFO CODE : 340600

Barcode: 8011399004182

Package dimension, Wid.-Dep.-Height (mm): 240 x 220 x 295

Package weight kg: 5.9

Pieces for pallet: 75

HS code: 85044055



FUSE 50 Amp

Ташев-Галвинг ООД
www.tashev-galving.com