



CLASS BOOSTER 220A



Input Voltage 1Ph 230 Volt
Battery 12 - 24 Volt, 20 > 300 Ah



Description

- Code: 341000

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- Charging current regulation**
- Overload protection**
- Inversions of polarity protection**
- Short circuits protection**
- Manual charge breaker**

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12 / 24V

Power (KW): 0,5 / 3Kw

Average charging current (Amp): 13,0A

Effective charging current (Amp): 20,0A

Battery capacity (Ah min/max): 20 / 300Ah

Charging positions (N°): 2

Boosting Current (Amp 0 Volt CC): 230A

Boosting current (Amp 1 Volt / EL): 150A

Weight Kg $\approx$: 11

Dimension, Wid.-Dep.-Height (mm): 340 x 300 x 160

LOGISTIC INFO CODE : 341000

Barcode: 8011399004212

Package dimension, Wid.-Dep.-Height (mm): 370 X 370 X 180

Package weight kg: 9.7

Pieces for pallet: 42

HS code: 85044055



FUSE 80 Amp

Ташев-Галвинг ООД
www.tashev-galving.com