



CLASS BOOSTER 400E



Input Voltage 1Ph 230 Volt
Battery 12 - 24 Volt, 35 > 500 Ah



Description

- Code: 354100

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- Charging current regulation
- Overload protection
- Inversions of polarity protection
- Short circuits protection
- Manual charge breaker

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12 / 24V

Power (KW): 1,3 / 6Kw

Average charging current (Amp): 26,0A

Effective charging current (Amp): 40,0A

Battery capacity (Ah min/max): 35 / 500Ah

Charging positions (N°): 4

Boosting Current (Amp 0 Volt CC): 400A 0V

Boosting current (Amp 1 Volt / EL): 270A 1V

Weight Kg $\approx$: 18

Dimension, Wid.-Dep.-Height (mm): 400 x 300 x 640

LOGISTIC INFO CODE : 354100

Barcode: 8011399010879

Package dimension, Wid.-Dep.-Height (mm): 595 x 310 x 265

Package weight kg: 19.6

Pieces for pallet: 24

HS code: 85044055

Optional accessories



FUSE 50 Amp



FUSE 80 Amp

Ташев-Галвинг ООД
www.tashev-galving.com