

MultiMeter Pocket XP



Professional multimeter

This robust professional multimeter allows precise measurement of voltage, current, resistance, capacitance, frequency and duty factor. The device has automatic range switching and manual range preselection options and is suitable for use in every area of building installation. The measured values can be easily transferred to a smartphone using the Digital Connection interface.

- High measurement resolution for precisely determining the most important electrical variables
- Automatic range changeover and manual range preselection
- Automatic continuity tester with acoustic signal
- Min/Max function
- Data Hold function
- Simple transfer of measured data through Digital Connection interface to mobile phone



TECHNICAL DATA

Measured Variable	Direct current / alternating current Direct voltage / alternating voltage Resistance Capacitance Frequency
Features	automatic / manual measuring range MAX MIN HOLD automatic switch-off
AC Voltage	Range / Resolution / Accuracy*: 4.000V / 1 mV / $\pm (1.0\% + 5)$ 40.00V / 10 mV / $\pm (1.0\% + 5)$ 400.0V / 0.1V / $\pm (1.0\% + 5)$ 600V / 1V / $\pm (1.2\% + 5)$ Bandwidth: 50 ... 60 Hz True RMS
DC Voltage	Range / Resolution / Accuracy*: 400.0 mV / 0.1 mV / $\pm (1.0\% + 8)$ 4.000V / 0.1 mV / $\pm (1.0\% + 3)$ 40.00V / 0.1 mV / $\pm (1.0\% + 3)$ 400.0V / 0.1 mV / $\pm (1.0\% + 3)$ 600V / 0.1V / $\pm (1.2\% + 3)$
Dimensions (W x H x D)	67 mm x 120 mm x 47 mm



SCOPE OF DELIVERY



Item No. 083.036A

GTIN (EAN) 4021563699391

SU 2