

Зарядно устройство Деса за акумулатор 12 V, 6 A, MACH 116



MACH 116



Input Voltage 1Ph 230 Volt
Battery 12 Volt, 20 > 90 Ah



Reverse
Polarity
Protect



Description

- Code: 302700

Portable battery charger

- Suitable for charging lead batteries: WET serviceable and maintenance free, AGM, Start & Stop
- Overload protection with automatic reset
- Inversions of polarity protection
- Short circuits on the clamps protection
- Manual charge breaker

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12V

Power (W): 80W

Average charging current (Amp): 4,0A

Effective charging current (Amp): 6,0A

Battery capacity (Ah min/max): 20 / 90Ah

Battery types: Automotive: Pb (WET - AGM)

Charging positions (N°): 1

Weight Kg \approx : 1.5

Dimension, Wid.-Dep.-Height (mm): 225 x 160 x 95

LOGISTIC INFO CODE : 302700

Barcode: 8011399015508

Package dimension, Wid.-Dep.-Height (mm): 165 x 105 x 230

Package weight kg: 2

Pieces for pallet: 318

HS code: 85044055

Продукт: [Зарядно устройство Деса за акумулатор 12 V, 6 A, MACH 116](#)

Категория: [Зарядни и стартерни устройства](#)

Бранд: [Деса](#)

Категория бранд: [Стартерно устройство Деса](#)