

Стартерно устройство Dеса с вграден акумулатор 600 А, 2.1 А, 12 V, FAST 20K



12-24V



12V

FAST 20K

2000A (peak)



12000J J-BME₃



12-24V

FAST 35K

3000A (peak)



20000J J-BME₃

Accessori in dotazione
Supplied accessories



	FAST 20K	FAST 35K
Tensione di alimentazione - Input voltage	1 Ph - 100/240V 50/60 Hz	
Tensione di avviamento - Boosting voltage	12V	12-24V
Corrente di avviamento max - Boosting current max	2000A	12V 1500A - 24V 2000A
Corrente di avviamento - Boosting current (1V/C)	600A	12V 700A - 24V 500A
Capacità batteria - Battery capacity	20000mAh	35000mAh
Tipo di batteria - Battery types	Automotive: Pb (WET - AGM - GEL) - Lithium (LiFePO ₄)	
J-BME ₃ (Joule-Battery Maximum Energy)	12000J	2000J
Avviamento cilindrate For engines up to T _a = 25°C	Benzina - Petrol	6000cc
	Diesel	4000cc
Uscita USB 1 - USB 1 output	5V - 2,1A	5V - 2,1A
Uscita USB 2 - USB 2 output	5V - 1,0A	5V - 1,0A
Uscita DC - DC output	-	12V - 10A
Ingresso - Input (Jack)	-	15V - 1A
Ingresso - Input (Micro-USB)	-	-
Ingresso - Input (USB type C)	5V - 1A	- Tempo
di carica - Charging time	7h	7h
Dimensioni - Dimensions	225 x 91 x 34	292 x 233 x 79
Peso - Weight	0,65 kg	2,7 kg
Versione - Version		
Con accessori - With accessories	381000	380900

Продукт: [Стартерно устройство Деса с вграден акумулатор 600 A, 2.1 A, 12 V, FAST 20K](#)

Категория: [Зарядни и стартерни устройства](#)

Бранд: [Deca](#)

Категория бранд: [Стартерно устройство Деса](#)