



CLASS BOOSTER 4500



Input Voltage 1Ph 230 Volt
Battery 12 - 24 Volt, 35 > 600 Ah



Description

- Code: 363400

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- Fast charging with timer**
- Overload protection**
- Short circuits protection**
- Inversions of polarity protection**
- Manual charge breaker**

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12 / 24V

Power (KW): 1,7 / 7,5Kw

Average charging current (Amp): 50,0A

Effective charging current (Amp): 75,0A

Battery capacity (Ah min/max): 35 / 600Ah

Charging positions (N°): 4

Boosting Current (Amp 0 Volt CC): 500A 0V

Boosting current (Amp 1 Volt / EL): 330A 1V

Weight Kg $\approx$: 25.5

Dimension, Wid.-Dep.-Height (mm): 470 x 320 x 750

LOGISTIC INFO CODE : 363400

Barcode: 8011399020342

Package dimension, Wid.-Dep.-Height (mm): 685 x 360 x 295

Package weight kg: 26

Pieces for pallet: 15

HS code: 85044055

Optional accessory



FUSE 100 Amp

Ташев-Галвинг ООД
www.tashev-galving.com